



HP Neverstop Laser MFP 1200a

High-volume laser printing at an ultra low cost, with MFP versatility and legendary HP quality.

Easily print at high volumes with HP's first toner tank printer³ – includes 5,000 pages of toner.¹ Count on HP quality at an ultra-low cost, plus MFP versatility. Easily restore toner levels with a mess-free experience.⁵



Up to 10x more pages than in-class HP lasers⁷

- Engineered for high-volume printing – get 5,000 pages of toner right out of the box.¹
- Get print speeds up to 20 ppm A4.⁴
- Breeze through tasks with versatile MFP performance – print, scan, and copy.
- Get quick and easy printing directly at the control panel.

Original HP quality. Unbelievable savings.

- Count on getting consistently superb prints this revolutionary laser.
- Produce sharp text and bold blacks.
- HP's innovative laser printer helps you to print at high volumes for an ultra low cost.

15-second, mess-free self reload³

- Easy reload your toner with a mess-free experience.³
- Quickly and easily restore toner levels with the toner reload kit.⁵

¹Actual yield varies considerably based on content of printed pages and other factors. Average based on ISO/IEC 19752 and continuous printing. For details see www.hp.com/go/learnaboutsupplies. ²Requires the HP Smart app download. For details on local printing requirements see www.hp.com/go/mobileprinting. ³HP internal research and Keypoint Intelligence-Buyers Lab 2018 study commissioned by HP. For details see www.keypointintelligence.com/HPNeverstop. ⁴Excludes first set of test documents. For more information, see www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity. ⁵Toner reload kit is not included with the printer; please purchase separately. ⁶Mobile device needs to be connected to Wi-Fi Direct® signal of a Wi-Fi Direct-supported AIO or printer prior to printing. Details at hp.com/go/mobileprinting. Wi-Fi Direct® is a registered trademark of Wi-Fi Alliance®. ⁷Based on HP LaserJet Pro M15 and HP LaserJet Pro MFP M28 with standard-fill HP 44A/48A Black Original LaserJet Toner Cartridge with ISO yield of 500 pages. Actual yield varies considerably based on content of printed pages and other factors. Average based on ISO/IEC 19752 and continuous printing. For details see www.hp.com/go/learnaboutsupplies.

HP Neverstop Laser MFP 1200a Technical specifications

Functions / Multitasking supported	Print, copy, scan / Yes
Print speed black	A4: Up to 20 ppm; First page out: As fast as 7.6 sec
Print resolution	Black (best): Up to 600 x 600 x 2 dpi; Black (fine lines): Up to 600 x 600 dpi
Print technology	Laser
Print resolution technologies	HP FastRes 1200 (600 x 600 x 2 dpi)
Standard print languages	PCLmS; URF; PWG
Printer smart software features	HP Auto-On/Auto-Off
Scan type / Technology	Flatbed
Scan resolution	Hardware: Up to 600 ppi; Optical: Up to 600 ppi
Scan file format	JPG, RAW (BMP), PNG, TIFF, PDF
Scan size maximum	Flatbed: 216 x 297 mm
Scanner advanced features	No
Bit depth / Grayscale levels	24-bit/256
Copy speed black	Copy speed: Up to 20 cpm
Copy resolution	Black (text and graphics): Up to 600 x 600 dpi (flatbed)
Maximum number of copies	Up to 99 copies
Copier settings	Number of Copies; Lighter/Darker; Optimize; Paper
Copier resize	25 to 400%
Standard connectivity	Hi-Speed USB 2.0
Wireless capability	No
Memory	Standard: 64 MB; Maximum: 64 MB
Processor speed	500 MHz / Hard disk: None
Duty cycle	Monthly A4: Up to 20,000 pages
Recommended monthly page volume	250 to 2500
Media types supported	Plain paper, Heavy paper, Bond paper, Label, Light paper, Envelope
Media weight supported	60 to 120 g/m ²
Media sizes supported	A6; A5; A4; Letter; No. 10 Env; C5 Env; DL Env; B5(UIS), Oficio 216x340; Legal; 105 x 148.5 to 216 x 356 mm
Media Sizes Custom	105 x 148.5 mm to 215.9 x 356 mm
Paper handling	Input Capacities: Up to 150 sheets Standard; Up to 1 envelope Output Capacities: Up to 100 sheets Standard Duplex Options: Manual (driver support provided) Standard paper trays: 1 input tray

What's in the box	4QD21A HP Neverstop laser MFP 1200a Printer; Preinstalled HP Black Original Imaging Drum (~5,000 pages yield, ~20,000 pages useful life); Reference guide; Setup guide; Regulatory flyer; Support flyer; Warranty guide; Power cord
Replacement cartridges²	HP 103A Black Original Neverstop Laser Toner Reload Kit (Yield ~2,500 pages); HP 103AD Dual pack Black Original Neverstop Laser Toner Reload Kit (Yield ~2x2,500 pages)
Product dimensions	W x d x h: 380.5 x 293.4 x 287 mm (14.98 x 11.55 x 11.3 in); Maximum: 380.5 x 385 x 521 mm (14.98 x 15.16 x 20.51 in)
Product weight	8.71 kg (19.20 lb)
Warranty features	HP one year hardware limited warranty. For full terms and conditions, visit: www.hp.com/go/orderdocuments .
Control panel	2-line icon LCD
Display description	2-line icon LCD
Software included	For Windows OS: HP Software Installer, HP Software Uninstaller (exclude Win8+), HP PCLmS Printer Driver, HP Device Experience (DXP), HP Web Services Assist (HP Connected), Device Setup & Software, Online user manuals, HP Printer Assistant, HP Scan Driver, HP Scan Application, HP Product Improvement Study. For Mac OS: Welcome Screen, (Directs users to HP.com or OS App Store for LaserJet Software)
Compatible operating systems	Windows® 10, 8.1, 8, 7; 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer, Apple® OS X El Capitan (v10.11) macOS Sierra (v10.1.2) macOS High Sierra, (v10.1.3); 1.5 GB HD; Internet required; USB Linux (For more information, see https://developers.hp.com/hp-linux-imaging-and-printing)
Compatible network operating systems	Windows® 10, 8.1, 8, 7; 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer, Apple® OS X El Capitan (v10.11) macOS Sierra (v10.1.2) macOS High Sierra, (v10.1.3); 1.5 GB HD; Internet required; USB Linux (For more information, see https://developers.hp.com/hp-linux-imaging-and-printing)
Minimum system requirements	PC: Windows® 10, 8.1, 8, 7; 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer, Mac: Apple® OS X El Capitan (v10.11) macOS Sierra (v10.1.2) macOS High Sierra, (v10.1.3); 1.5 GB HD; Internet required; USB
Power²	Power supply type: Internal (Built-in) power supply; Power requirements: 110V - 127V nominal @ +/-10% (min 99V, max 140V), 50 - 60Hz nominal +/- 3Hz (min 47Hz, max 63Hz); Power consumption: 325 watts (Active Printing), 3.2 watts (Ready), 0.6 watts (Sleep), 0.1 watts (Manual off)
Acoustics	Acoustic power emissions: 6.5 B(A); Acoustic pressure emissions: 51 dB(A)
Operating environment	Operating temperature range: 15 to 32.5°C; Recommended operating temperature: 17.5 to 25°C; Storage temperature range: -20 to 40°C; Non-operating humidity range: ; Operating humidity range: 10 to 80% RH, Recommended humidity operating range: 30 to 70% RH
HP Service and Support options	UB4X8E - HP 2y Onsite Exchange NS L 1xxx MFP SVC; UB4X9E - HP 3y Onsite Exchange NS L 1xxx MFP SVC; UB4Y0E - HP 4y Onsite Exchange NS L 1xxx MFP SVC; UB4Y1E - HP 2y NBD Exchange NS L 1xxx MFP SVC; UB4Y2E - HP 3y NBD Exchange NS L 1xxx MFP SVC; UB4Y3E - HP 4y NBD Exchange NS L 1xxx MFP SVC; UB4Y4E - HP 2y Std Exchange NS L 1xxx MFP SVC; UB4Y5E - HP 3y Std Exchange NS L 1xxx MFP SVC; UB4Y6E - HP 4y Std Exchange NS L 1xxx MFP SVC; UB4Y7E - HP 2y Return to Depot NS L 1xxx MFP SVC; UB4Y8E - HP 3y Return to Depot NS L 1xxx MFP SVC; UB4Y9E - HP 4y Return to Depot NS L 1xxx MFP SVC

Learn more at hp.com

¹ HP Black Original Laser Imaging Drum (introductory ~5,000 page black toner yield provided, with ~20,000 page Imaging Drum useful life). Actual yields vary considerably based on images printed and other factors. For details see <http://www.hp.com/go/learnaboutsupplies> ² Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Power consumption values typically based on measurement of 115 V device. ³ Declared black toner page yield value in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see <http://www.hp.com/go/learnaboutsupplies>. HP W1103A and HP W1104A replacement supplies are not imported, sold, nor warranted in China. ⁴ Declared black toner page yield value in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see <http://www.hp.com/go/learnaboutsupplies>. HP W1103A and HP W1104A replacement supplies are not imported, sold, nor warranted in China. ⁵ HP SureSupply alerts you when your Imaging Drum is running low and helps you purchase online or locally through HP or a participating retailer. Only available with Original HP supplies; Internet access required. To learn more, visit <http://www.hp.com/go/SureSupply> ⁶ Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on measurement of 115 V device.

